

16. A method for transferring data streams of different transmission rates between a first and a second data transmission unit as claimed in Claim 13, the method further comprising the steps of:

inserting, into each of the first to fifth sub-frames of a data frame, 14 data bit groups each having a data volume of 14 bits and each followed by a fixed stuffing bit, and a data bit group having a data volume of 15 bits;

inserting, into the sixth sub-frame of the data frame, a data bit group having a data volume of 12 bits and followed by a fixed stuffing bit, 13 data bit groups each having a data volume of 14 bits and each followed by a fixed stuffing bit, and a data bit group having a data volume of 15 bits; and

transferring data bits of a first and a second 1.250 Gbps signal, at least partially bit interleaved, as user data in the data bit groups.

#### REMARKS

The present amendment makes editorial changes and corrects typographical errors in the Specification, which includes the Abstract, in order to conform the Specification to the requirements of United States Patent Practice. No new matter is added thereby. Attached hereto is a marked-up version of the changes made to the Specification by the present amendment. The attached page is captioned **"Version With Markings To Show Changes Made"**.

In addition, the present amendment cancels original claims 1-8 in favor of new claims 9-16. Claims 9-16 have been presented solely because the revisions by crossing-out and underlining which would have been necessary in claims 1-8 in order to present those claims in accordance with preferred United States Patent Practice would have been too extensive, and thus would have been too burdensome. The present amendment is intended for clarification purposes only and not for substantial reasons related to patentability pursuant to 35 U.S.C. §§103, 102, 103 or 112. Indeed, the cancellation of claims 1-8 does not constitute an

intent on the part of the Applicant to surrender any of the subject matter of claims  
1-8.

Early consideration on the merits is respectfully requested.

Respectfully submitted,

5

BELL, BOYD & LLOYD LLC

10

BY



William E. Vaughan

Reg. No. 39,056

P.O. Box 1135

Chicago, Illinois 60690-1135

Phone: (312) 807-4292

15

09937918 "100101

VERSION WITH MARKINGS TO SHOW CHANGES MADE

Description

Method for transferring data streams, having different data transmission rates,  
between a first and second data transmission unit

5

SPECIFICATION

TITLE OF THE INVENTION

METHOD FOR TRANSFERRING DATA STREAMS OF DIFFERENT  
TRANSMISSION RATES BETWEEN A FIRST AND SECOND  
TRANSMISSION UNIT

10

BACKGROUND OF THE INVENTION

In order to utilize better the transmission capacity available in  
communications networks, in particular optical communications networks,  
multiplexers are used to multiplex input-end channels in wavelength multiplexers.  
These multiplexers make it possible, on the one hand, to make better use of the  
bandwidth of the optical channels and, on the other hand, to reduce the number of  
selective lasers necessary for wavelength multiplexing.

Contemporary multiplexers, in particular multiplexers used in SONET/SDH  
data transmission, are costly and very complex. Such multiplexers have the  
disadvantage that they only permit data streams or SDH data signals which are  
configured in accordance with the synchronous digital hierarchy SDH to be  
multiplexed, the multiplexers being configured in accordance with the ITU  
Recommendation G.707.

The present invention is ~~based on the object of~~ directed toward achieving  
maximum or effective use of the transmission capacity made available by the  
communications network when a ~~plurality~~ number of data streams having different  
data transmission rates are transmitted over a communications network; in  
particular, over an optical communications network. ~~The object is achieved by~~  
~~means of a method based on a method according to patent claim 1, by means of its~~  
~~characterizing features.~~

## SUMMARY OF THE INVENTION

In the method according to the present invention, data streams having different transmission rates are transferred between a first and second data transmission unit, the data streams to be transferred being inserted into data frames each having the same data volume and the same data transmission rate. The An essential aspect of the method according to the present invention is that the data frames each have six subframes, a first and second stuffing check bit being arranged at the start of each of the second to sixth subframes. A first and second variable stuffing bit is arranged in the sixth subframe, following the first and second stuffing check bits. The data frames each have a data volume of 1360 bits.

The An essential advantage of the method according to the invention is that it is possible to implement a transparent transmission of data streams having any desired data transmission rates, or a transparent transmission of information which is transferred using any desired data transmission method and has any desired data formats. Furthermore, optimum, i.e. or maximum use of the transmission capacity made available by a communications network and/or optimum use of the bandwidth of a data transmission channel made available for transferring information is achieved. By using a uniform data frame it is possible to dispense with complex pointer methods in multiplexers. Moreover, it is possible to reduce the number of selective lasers at the input of wavelength multiplexers which make available a data transmission channel.

Additional features and advantages of the present invention are described in, and will be apparent from, the following Detailed Description of the Invention and the Figures.

~~Further advantageous refinements of the method according to the invention can be found in the further claims.~~

~~The method according to the invention will be explained in more detail below with reference to a plurality of drawings, in which:~~

## BRIEF DESCRIPTION OF THE FIGURES

FIG 1 shows a detail of a data transmission path.

FIG 2 shows a data frame for multiplexing a 2.666057 Gbps data stream.

FIG 3 shows a data frame for multiplexing a 2.488320 Gbps data stream.

FIG 4 shows a data frame for multiplexing 1.250 Gbps data streams.

FIG 5 shows a multiplex structure for forming the multiplex signal.

FIG 6 shows a data frame for a multiplex signal.

#### DETAILED DESCRIPTION OF THE INVENTION

FIG 1 shows a detail from a data transmission system in which wavelength multiplexers are arranged for, for example, N x 10 Gbps channels. In the data transmission system illustrated, a first data transmission unit representing a terminal multiplexer MUXE is arranged, ~~by means of~~ via which data signals or data streams e1, e2, e31, e32 which are present at inputs EM1...4 and have different data transmission rates are combined.

For this exemplary embodiment it will be assumed that a data signal e1 having a data transmission rate of 2.666057 Gbps or a data stream e1 having a data transmission rate of 2.666057 Gbps is fed to the first input EM1 of the multiplexer MUXE. This data signal or data stream is specified by the ITU-T in the Recommendation G.975 and describes an STM-16/OC-48 signal with FEC (Forward Error Correction). A 2.488320 Gbps data signal e2 or a data stream e2 having a transmission rate of 2.488320 Gbps is fed to the second input EM2 of the multiplexer MUXE. This data signal e2 is specified by the ITU-T in the Recommendation G.707 and describes an STM-16/OC-48 signal. Furthermore, in each case a 1.250 Gbps data signal or in each case a data stream e31, e32 having a data transmission rate of 1.250 Gbps is fed to the third and fourth inputs of the multiplexer MUXE. This data signal e31, e32 is specified BY IEEE P 802.3 and describes a data signal referred to as "Gigabit-Ethernet".

The output signal which is present at the output AM of the terminal multiplexer MUXE is passed on to a wavelength multiplexer WDM. The data which is directed via a wavelength multiplexer WDM is transmitted, for example, via optical or electric amplifiers OA, ER and further wavelength multiplexers WDM, to a data transmission unit which is arranged at the end of the data transmission system and also represents a terminal multiplexer MUXA.

The data signals or data streams e1, e2, e31, e32 which are present at the four inputs EM1...4 are each inserted into data frames, also referred to as containers, DR1...3 using a frame forming unit (not illustrated) which is arranged in the multiplexer MUXE, the data frames DR1...3 each having the same data volume and the same data transmission rate. The data frames DR1...3 which are formed and the data signals e1, e2, e31, e32 which are inserted into the data frames DR1...3 are subsequently multiplexed by the multiplexer MUXE and converted into a multiplex signal a which represents the output signal.

FIG 2 illustrates a first data frame DR1 for multiplexing the 2.666057 Gbps data signal e1 (STM-16/OC-48 with FEC). The 2.666 Gbps data signals e1 which are specified in accordance with the Recommendation G.975 can be plesiochronous with respect to one another and when they are they can have a maximum deviation from the setpoint frequency of 4.6 ppm (parts per million). The first data frame DR1 has 6 subframes UR1...6. In the first subframe UR1, 225 data bits of the 2.666 Gbps data signal e1 are transmitted as user data nd. A first and second stuffing check bit C1, C2 are arranged at the start of each of the second to sixth subframes UR2...6. In the sixth subframe UR6, a first and second stuffing bit S1, S2 are additionally arranged following the two stuffing check bits C1, C2. 225 databits are transmitted in each of the second to fifth subframes UR2...5 following the two stuffing check bits C1, C2, and 223 data bits of the 2.66 Gbps data signal e1 are transmitted as user data nd in the sixth subframe UR6 following the two stuffing check bits C1, C2 and the two stuffing bits S1, S2.

The first data frame DR1 has in total a data volume of 1360 bits, of which, depending on the status or use of the two stuffing bits S1, S2, 1348 to 1350 bits can be used for transferring data bits of the 2.666 Gbps data signal e1 as user data nd. In order to permit the data signal e1 present at the first input EM1 of the multiplexer MUX to be multiplexed, a stuffing method is used. For example, a positive stuffing method can be used. In this stuffing method, the stuffing information is transmitted in the first and second stuffing check bits C1, C2, the first and second stuffing check bits C1, C2 each indicating whether or not the two stuffing bits S1, S2 are filled with user information. For example, if the bit

combination “00000” is assigned to the first stuffing check bits C1, this indicates that the first stuffing bit S1 is used to transfer data bits of the data signal e1. If the bit combination “11111” is assigned to the first stuffing check bits C1, this indicates that the first stuffing bit S1 is a stuffing bit. In order to protect against individual bit errors in the stuffing check bits C1, C2 arranged in the first data frame DR1, a majority decision is advantageously carried out.

Depending on the use or status of the two stuffing bits S1, S2 arranged in the first data frame DR1, 1348 to 1350 data bits of the first data signal e1 are transmitted as user data nd by the first data frame DR1. When a positive stuffing method is used, the data transmission rate of the first data frame DR1 is selected such that in the nominal case, 1349 user data bits nd are transmitted per data frame. This leads to a nominal bit rate of the first data frame DR1 of 2.666057 Gbps x 1360 bits / 1349 bits = 2.687796 Gbps.

The stuffing method used thus permits fluctuation of the data transmission rate of the data signal e1 inserted into the first data frame DR1 within the following limits  $f_o$ ,  $f_u$ :

$$f_o = 2.687796 \text{ Gbps} \times 1350 \text{ bits} / 1360 \text{ Bits} = 2.668032 \text{ Gbps}$$

$$f_u = 2.687796 \text{ Gbps} \times 1348 \text{ bits} / 1360 \text{ bits} = 2.664080 \text{ Gbps}.$$

The derived limits  $f_o$ ,  $f_u$  of the data transmission rate of the first data signal e1 correspond to an acceptable deviation of  $2.668032 / 2.666057 = 1.000741$ , which corresponds to an acceptable deviation of 741 ppm. This is higher than the maximum frequency deviation of a transmission signal of 4.6 ppm which is permitted in accordance with ITU Recommendation G.813, page 3, chapter 5.

FIG 3 illustrates a second data frame DR2 for multiplexing the 2.488320 Gbps data signal e2. For the second data frame DR2 which also has six subframes UR1...6, the same stuffing method as in the first data frame DR1 is used. In contrast to the first data frame DR1 illustrated in FIG 2, in the case of the second data frame DR2 fifteen times fourteen data bits 14D of the second data





$$f_u = 2.687796 \text{ Gbps} \times 632 \text{ bits}/1360 \text{ bits} = 1.249035 \text{ Gbps}$$

The derived limits  $f_0$ ,  $f_u$  of the data transmission rates of the two Gigabit-Ethernet signals e31, e32 correspond to an acceptable deviation of 1.250/1.249035 = 1.000772, which corresponds to an acceptable deviation of 772 ppm.

FIG 5 illustrates in a self-explanatory fashion a multiplex structure for forming a multiplex signal. By way of example, it will be assumed that in each case four frame signals each representing one of the data frames DR1...3 are multiplexed in any desired combination to form a multiplex signal as. According to FIG 5, the four input signals e1, e2, e31, e32 are inserted into the corresponding data frames DR1...3 as a function of their data transmission rate, the data transmission rates of the inserted data signals e1, e2, e31, e32 being adapted to the uniform data transmission rate of the data frames DR1...3 by inserting fixed stuffing bits and ~~by means of~~ via the stuffing method described. The data frames DR1...3 formed are then bit interleaved using ~~multiplex means~~ multiplexer AUG. In a following frame forming unit STM<sub>1</sub> for example a "synchronous transport module" STM<sub>1</sub> a frame alignment word RKW and corresponding overhead information OU are added to the interleaved data signal or data stream and the multiplex signal as is formed therefrom.

20           The multiplex signal as which is formed is subsequently transferred via the communications network to the destination multiplexer MUXA which is illustrated in FIG 1 and in which the received multiplex signal as is demultiplexed again into the data frames DR1...3 or into the data signals e1, e2, e31, e32 inserted therein.

FIG. 6 illustrates an exemplary refinement of the multiplex signal as  
 25 formed. At the start of the multiplex signal as, the frame alignment word RKW,  
 which has a data volume of 16 bits, is arranged. The overhead information OH  
 having a data volume of 8 bits is arranged following the frame alignment word  
 RKW.

The multiplex signal as illustrated is also subdivided into six subframes  
 30 UR1...6, the six subframes having in total a data volume of 5464 bits. The data bits  
 of any desired combination of four data frames DR1...3 which are formed are

inserted after bit interleaving into the six subframes UR1...6. ~~By means of~~ Via the bit interleaving of any respective desired combination of four data frames DR1...3 which are formed, the respective subframes UR1...6 of the four data frames C1...4 are correspondingly combined or multiplexed; for example, the respective first  
5 subframes UR1 of the four data frames DR1...3 which are combined in the multiplex signal as are arranged in bit-interleaved form in the first subframe UR1 of the multiplex signal as. The first and second stuffing check bits C1, 2 which are arranged in each of the second to sixth subframes UR2...6 of the multiplexed data frames DR1...3 are arranged at the start of each of the second to sixth subframes  
10 UR1...6 of the multiplex signal as, and the first and second stuffing bits S1,2 of the multiplexed data frames DR1...3 are correspondingly subsequently arranged in the sixth subframe UR6 of the multiplex signal.

The data transmission rate of the multiplex signal as is obtained as:

15  $f_m = 2.687796 \text{ Gbps} \times 5464/1360 = 10.798616 \text{ Gbps}$

It is to be noted that any desired data frames DR1...3 with any desired data volume and data transmission rates can be formed using the method according to the present invention, the data frames DR1...3 being multiplexed to form any  
20 desired multiplex signals as. As a result, optimum input signals which are adapted to the transmission channels of the wavelength multiplexers can be provided for the wavelength multiplexers. For example, according to one ~~refinement variant~~  
embodiment (not illustrated) eight of the input signal e1, e2, e31, e32 described are fed to the multiplexer MUXE, the input signals e1, e2, e31, e32 which are fed in  
25 being multiplexed to form a 20 Gbps multiplex signal as.

Although the present invention has been described with reference to specific embodiments, those of skill in the art will recognize that changes may be made thereto without departing from the spirit and scope of the invention as set forth in the hereafter appended claims.

09939100-100101

**Method for transferring data streams, having different data transmission rates, between a first and second data transmission unit**

5 Data streams (~~e1, e2, e31, e32~~) each having different data transmission rates are inserted into data frames (~~DR1...3~~) each having the same data volume and the same data transmission rate. The data frames (~~DR1...3~~) each have six subframes (~~UR1...6~~). A first and second stuffing check bit (~~C1, 2~~) are arranged at the start of each of the second to sixth subframes (~~UR2...6~~). A first and second variable  
10 stuffing bit (~~S1, 2~~) are arranged in the sixth subframe, following the first and second stuffing check bit (~~C1, 2~~). The data frames (~~DR1...3~~) each have a data volume of 1360 bits. A transparent transmission of data streams or data signals having any desired data transmission rates is advantageously carried out over a transmission channel, optimum utilization of the transmission capacity of the  
15 transmission channel being achieved.

24